

Tuotetiedot							
Tuotekoodi	Tuotenimi	I _n Al	I _n Cu	U _n	USA spesifiset		
					I _{max} Al	I _{max} Cu	U _{max}
VC02-0149	OT-yleiskaapelikenkä 2xAl/Cu 95-300mm ²	630 A	980 A	690 V	-	-	-

Yleistä	Johtimien asennus
<p>OT-yleisliittimet ovat tarkoitettu alumiini- ja kuparikaapeleiden liittämiseen.</p> <ul style="list-style-type: none"> - Sektorikaapeli on muokattava pyöreäksi ennen asennusta. Esimuokkaus siirtoleukapihdeillä ennen eristyksen poistamista tai pyörästysleuoilla eristyksen poistamisen jälkeen. - Poista eristys kaapelista. Ks. kuorintapitus L taulukosta alapuolella. - Poista mahdollinen oksidikerros messinki- tai teräsharjalla. - Liitin on esirasvattu liitosrasvalla. 	<p>Tue liitin kiristyksen ajaksi.</p> <p>Kiristä liitinruuvit alla mainittuun kiristysmomenttiin M.</p> <p>Varmista liitinruuvien kireydet ensimmäisten momenttiin kiristyksien jälkeen. Tee tarvittaessa jälkikiristys.</p> <p>Asennettaviin johtimiin ei saa kohdistua vetojännitystä.</p> <p>MAX. 2x185 AL, 2x300CU</p>

Kytkenä			
Ruuvien koko	Ruuvi	M22	Kiristysmomentti M
	AV	8	95-150 mm ² 30 Nm
			185-300 mm ² 60 Nm
			Kuorintapitus L 39±1 mm
			Johtimet 2xAl/Cu 95-300 mm²
Kuparijohtimet	Alumiinijohtimet	Sallitut IEC 60228 -johdintyytit	
Max. 3 X CU / Liitinaukko	1 X AL / Liitinaukko	Class 5 & 6 (hienosäikeinen) Suositellaan johdinpääholkkia	
		Class 1 & 2 (yksi- ja muutamalankainen)	
≤ 300 mm ² yhteensä	Liitosrasva: esim. Penetrox	Sektorikaapeli	
		Muokkaa pyöreäksi	

Asennus virtakiskoon	Huomi!
<ul style="list-style-type: none"> - Kun kytket liittimen virtakiskoon, varmistu että liitospinnat ovat puhtaat ja reikien reunoilla ei ole purseita. - Käytä kuvan mukaisia tai vastaavia kiinnitystarvikkeita. - Suositus kiristysmomentti 50-75 Nm <p>Huom! Ruuvien pituus riippuu virtakiskon paksuudesta.</p> <p>M12/8.0/DIN 934 D12/DIN 6796 ; SFS 3737 D12/SFS 3738 D12/SFS 3738 M12/8.8/DIN 933</p>	<p>Liittäessä alumiinikiskoon on kiskon pinta harjattava teräsharjalla ja välittömästi käsiteltävä liitosrasvalla. Kosteissa tiloissa suojarasvan käyttö on suositeltavaa (esim. Penetrox)</p> <p>Kiskon puolella on käytettävä paineentasauslaatan lisäksi kartiomaista puristuslaattaa (esim. DIN 6796).</p>

Johdintaulukko, poikkipinta-ala ja johtojen määrä / kytkentätila (Al-johtimien määrä suluisissa)										
1,5 mm ²	2,5 mm ²	6 mm ²	10 mm ²	16 mm ²	25 mm ²	35 mm ²	50 mm ²	Taulukossa olevat johtimien luvut tarkoittavat vain tehdasmaisesti asennettuja liittimiä.		
-	-	-	-	-	-	-	-			
			70 mm ²	95 mm ²	120 mm ²	150 mm ²	185 mm ²	240 mm ²	300 mm ²	400 mm ²
			-	3 (1)	2 (1)	2 (1)	1 (1)	1 (1)	1 (1)	-

Product data							
Product code	Product name	I _{n Al}	I _{n Cu}	U _n	US specific		
					I _{max Al}	I _{max Cu}	U _{max}
VC02-0149	OT Universal connector 2xAl/Cu 95-300mm ²	630 A	980 A	690 V	-	-	-

General	Conductor installation
<p>OT-Connectors are suitable for Aluminium- and Copper conductors.</p> <ul style="list-style-type: none"> - Segmental conductors have to be rounded before mounting. Pre-shape the sector conductor with transfer jaw pliers before removing the insulation or with rounding jaws after removing the insulation. - For stripping cable, see stripping length L (table below) - Remove any layer of oxide by brass or steel brush. 	<p>Support connector during tightening.</p> <p>Tighten the screw to the tightening torque M mentioned below. Ensure the torque after tightening. Tighten screws twice if necessary.</p> <p>Connector must be installed so that conductors are relieved from strain.</p>

CE RoHS

MAX. 2x185 AL, 2x300CU

Connection							
	Screw	Screw	M22	Tightening torque M	95-150 mm ²	30 Nm	Stripping length L 39±1 mm
		SW	8		185-300 mm ²	60 Nm	
				Conductor range	2xAl/Cu 95-300 mm²		
Copper conductors	Aluminium conductors	Supported IEC 60228 -conductors				Sector shaped cable	
Max. 3 X CU / Conductor contact space ≤ 300 mm ² total	1 X AL / Conductor contact space Anti-corrosion paste: e.g. Penetrox	 Class 5 & 6 (fine stranded) Using ferrule is recommended Class 1 & 2 (solid and stranded)	 Pre-round the cable				

Mounting to busbar	Attention
<ul style="list-style-type: none"> - Be sure that there are no burrs around the hole. - Length of the screw depends on the busbar thickness. - Use standard screws, nuts and washers. (Plated with Zn) - Recommended torque for M12 is 50-75 Nm. 	<p>When connecting to an aluminium rail, the surface of the rail must be brushed with a wire brush and immediately treated with connecting grease. In damp areas, the use of protective grease is recommended (eg. Penetrox). On the rail side, in addition to the pressure relief plate, a conical press plate (eg. DIN 6796) must be used.</p>

Cross section and max. number of Cu- conductors / contact space (Al- conductors in parenthesis)										
1,5 mm ²	2,5 mm ²	6 mm ²	10 mm ²	16 mm ²	25 mm ²	35 mm ²	50 mm ²	The specified max. amount of conductors refers only to industrially installed terminals.		
-	-	-	-	-	-	-	-			
			70 mm ²	95 mm ²	120 mm ²	150 mm ²	185 mm ²	240 mm ²	300 mm ²	400 mm ²
			-	3 (1)	2 (1)	2 (1)	1 (1)	1 (1)	1 (1)	-