

## LIVE - LINE CONNECTOR SL 30

<b>TECHNICAL DATA</b>	Type	SL 30
	Main conductor	Al 25 - 150 mm <sup>2</sup>
	Branch conductor	Al 25 - 150 mm <sup>2</sup>
	Screws	Eye screw M12 and 2 x M16x1,5
	Weight	450 g
	Tightening torque	40 Nm / 44 Nm

**USE** Live-line clamp is used for branching the line or connecting / disconnecting the transformer live.

### CONSTRUCTION

Component	Material
Body	Corrosion resistant aluminium alloy, tensile strength 300 N/mm <sup>2</sup>
Screws	Stainless steel and aluminium

The contact surfaces are brushed and greased to prevent oxidation.

### INSTALLATION

The live-line connector can be installed with standard live-line sticks. The screws have to be tightened to torque of 40 Nm (main) and 44 Nm (branch).

### TOOLS REQUIRED

Torque wrench ST 30  
Live-line stick

**MARKINGS** SL 30  
40 Nm / 44 Nm  
Al 25-150 / 25-150 mm<sup>2</sup>

**STANDARD** SFS 2663

**PACKING** 25 pcs in a cardboard box. Each connector is individually packed in a plastic bag.



