## **Product Environmental Profile**


#### WISER SMOKE ALARM





# Ceneral information Representative product WISER SMOKE ALARM - CCT599001 Description of the product High-end connected smoke alarm for global markets which can be integrated into the WISER system and also support temperature alarming and have the interconnection between devices even without gateway. Functional unit To provide high level alarming to notify people when device detect smoke in the located area, to support temperature detection and provide alarming if temperature is higher than its threshold during 10 years and 99.999% use rate, in accordance with EN 14604. -Standby:20µA -Active: 100mA

#### Constituent materials



#### **Substance assessment**

Products of this range are designed in conformity with the requirements of the RoHS directive (European Directive 2011/65/EU of 8 June 2011) and do not contain, or only contain in the authorised proportions, lead, mercury, cadmium, hexavalent chromium or flame retardants (polybrominated biphenyls - PBB, polybrominated diphenyl ethers - PBDE) or phthalates (Bis(2-ethylhexyl) phthalate DEHP, Butyl benzyl phthalate - BBP, Dibutyl phthalate – DBP, Diisobutyl phthalate - DIBP) as mentioned in the Directive.

Details of ROHS and REACH substances information are available on the Schneider-Electric Green Premium website <a href="http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium/green-premium.page">http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page</a>


### Additional environmental information

	The WISER SMOKE ALARM presents the following relevent environmental aspects				
Manufacturing	Manufactured at a Schneider Electric production site ISO14001 certified				
	Weight and volume of the packaging optimized, based on the European Union's packaging directive				
Distribution	Packaging weight is 167.3 g, consisting of Cardboard (59.4%), Paper (40.6%)				
Installation	Ref CCT599001 does not require any special installation.				
Use	The product does not require special maintenance operations.				
	End of life optimized to decrease the amount of waste and allow recovery of the product components and materials				
	This product contains Electronic card (51.81g), Battery (22.82g) that should be separated from the stream of waste so as to optimize end-of-life treatment.				
End of life	The location of these components and other recommendations are given in the End of Life Instruction document which is available on the Schneider-Electric Green Premium website				
	http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page				
	Recyclability potential:12%Based on "ECO'DEEE recyclability and recoverability calculation method" (version V1, 20 Sep. 2008 presented to the French Agency for Environment and Energy Management: ADEME).				

### $\mathcal{O}$ Environmental impacts

Reference life time	10 years				
Product category	Other equipments - Active proc	luct			
Installation elements	No special components needed				
Use scenario	The product is in standby mode 99.999% of the time with a power use of 0.00006w and in active mode 0.001% of the time with a power use of 0.3W, for 10 years.				
Geographical representativeness	European and Australia				
Technological representativeness	The Modules of Technologies s used in this PEP analysis (LCA technologies used to make the	-EIME in this case) are Simil			
	Manufacturing	Installation	Use	End of life	
Energy model used	Energy model used: China	Electricity Mix; AC; consumption mix, at consumer; < 1kV; EU-27. Electricity mix; AC; consumption mix, at consumer; 240V; AU.	Electricity Mix; AC; consumption mix, at consumer; < 1kV; EU- 27. Electricity mix; AC; consumption mix, at consumer: 240V; AU.	Electricity Mix; AC; consumption mix, at consumer; < 1kV; EU- 27. Electricity mix; AC; consumption mix, at consumer: 240V; AU.	

Compulsory indicators		WISER SMC	KE ALARM - CCT	599001			
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to mineral resources depletion	kg Sb eq	1.05E-03	1.05E-03	0*	0*	0*	0*
Contribution to the soil and water acidification	$kg SO_2 eq$	3.16E-02	3.13E-02	1.93E-04	3.77E-05	1.55E-05	9.08E-05
Contribution to water eutrophication	kg PO4 <sup>3-</sup> eq	9.25E-03	9.16E-03	4.44E-05	9.17E-06	1.29E-06	3.84E-05
Contribution to global warming	kg $\rm CO_2$ eq	9.43E+00	9.26E+00	4.22E-02	9.06E-03	4.70E-03	1.10E-01
Contribution to ozone layer depletion	kg CFC11 eq	1.24E-06	1.23E-06	0*	0*	4.33E-10	4.86E-09
Contribution to photochemical oxidation	kg $C_2H_4$ eq	2.18E-03	2.15E-03	1.38E-05	2.82E-06	1.01E-06	8.55E-06
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Net use of freshwater	m3	4.35E-01	4.35E-01	0*	0*	0*	7.33E-05
Total Primary Energy	MJ	1.35E+02	1.33E+02	5.97E-01	1.18E-01	7.81E-02	4.38E-01
ENVPEP2108022_V1		Internal					09/202



Manufacturing Distribution Installation Use

Use End of life

Optional indicators		WISER SMO	KE ALARM - CCT	599001			
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to fossil resources depletion	MJ	1.02E+02	1.01E+02	5.93E-01	1.17E-01	5.93E-02	3.39E-01
Contribution to air pollution	m³	7.52E+02	7.46E+02	1.80E+00	3.61E-01	3.65E-01	3.63E+00
Contribution to water pollution	m³	9.83E+02	9.69E+02	6.94E+00	1.37E+00	2.09E-01	5.17E+00
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Use of secondary material	kg	6.40E-03	6.40E-03	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	6.41E+00	6.41E+00	7.96E-04	0*	3.54E-03	0*
Total use of non-renewable primary energy resources	MJ	1.28E+02	1.27E+02	5.96E-01	1.18E-01	7.46E-02	4.38E-01
Use of renewable primary energy excluding renewable primary energy used as raw material	MJ	3.28E+00	3.28E+00	7.96E-04	0*	3.54E-03	3.99E-04
Use of renewable primary energy resources used as raw material	MJ	3.13E+00	3.13E+00	0*	0*	0*	0*
Use of non renewable primary energy excluding non renewable primary energy used as raw material	MJ	1.24E+02	1.23E+02	5.96E-01	1.18E-01	7.46E-02	4.38E-01
Use of non renewable primary energy resources used as raw material	MJ	3.85E+00	3.85E+00	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Waste categories	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Hazardous waste disposed	kg	8.56E+00	8.15E+00	0*	0*	0*	4.07E-01
Non hazardous waste disposed	kg	9.60E+00	9.59E+00	1.50E-03	1.23E-03	6.60E-03	4.61E-03
Radioactive waste disposed	kg	4.74E-03	4.73E-03	1.07E-06	0*	4.99E-06	2.85E-06
Other environmental information	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Materials for recycling	kg	2.16E-01	2.84E-02	0*	1.66E-01	0*	2.12E-02
Components for reuse	kg	0.00E+00	0*	0*	0*	0*	0*
Materials for energy recovery	kg	2.71E-02	0*	0*	0*	0*	2.71E-02
Exported Energy	MJ	5.29E-04	4.97E-05	0*	4.79E-04	0*	0*

\* represents less than 0.01% of the total life cycle of the reference flow

Life cycle assessment performed with EIME version EIME v5.9.1, database version 2016-11 in compliance with ISO14044.

The manufacturing phase is the life cycle phase which has the greatest impact on the majority of environmental indicators (based on compulsory indicators).

#### ENVPEP2108022\_V1 - Product Environmental Profile - WISER SMOKE ALARM

Please note that the values given above are only valid within the context specified and cannot be used directly to draw up the environmental assessment of an installation.

Registration number	ENVPEP2108022_V1	Drafting rules	PCR-ed3-EN-2015 04 02
Date of issue	09/2021	Supplemented by	PSR-0005-ed2-EN-2016 03 29
Validity period	5 years	Information and reference documents	www.pep-ecopassport.org
Independent verification	of the declaration and data		
Internal X	External		
The elements of the pre-	sent PEP cannot be compared with e	elements from another program.	
Document in compliance environmental labelling)		tal labels and declarations - Self-declare	d environmental claims (Type II
Schneider Electric Industrie	s SAS		
Country Customer Care Ce	ntor		
,			
http://www.schneider-electr			
http://www.schneider-electr 35, rue Joseph Monier			
http://www.schneider-electr 35, rue Joseph Monier CS 30323 F- 92506 Rueil Malmaison	ic.com/contact		
http://www.schneider-electr 35, rue Joseph Monier CS 30323	ic.com/contact Cedex		
http://www.schneider-electr 35, rue Joseph Monier CS 30323 F- 92506 Rueil Malmaison RCS Nanterre 954 503 439	ic.com/contact Cedex €	d by Schneider Electric	