

Shelly Wall Display X1i

Smart control panel, 4 inch

EAN code, Black: 3800238073039
EAN code, Silver: 3800238073046



Product description

The Shelly Wall Display X1i is a 4" touch control panel that brings control and monitoring of connected Shelly devices together on the wall. It replaces the original Shelly Wall Display, with a faster processor and Wi-Fi 6 on both 2.4 and 5 GHz.

It mounts in a standard European back box on 100-240 V~, or runs on USB-C where no fixed installation is wanted. An interchangeable one-output power base with a 5 A relay is included and can be swapped for the 2-Output Power Base or the Dimmer Power Base.

Built-in temperature, humidity, light, proximity and gesture sensors, a 1 W speaker, Bluetooth 5.0 and thermostat functionality. Available with a black frame or a silver aluminium frame with white front.

Technical data

Physical	
Size (HxWxD):	With base 86 x 86 x 36 mm / 3.39 x 3.39 x 1.42 in Without base 86 x 86 x 11 mm / 3.35 x 3.35 x 0.43 in
Weight:	With base 162 g / 5.7 oz, without base 112 g / 3.9 oz
Display:	4" colour touch screen, 5-point capacitive
Frame color:	Black / Silver aluminium with white front
Screw terminals max torque:	0.4 Nm / 3.5 lbin
Environmental	
Ambient working temperature:	-20 °C to 40 °C / -5 °F to 105 °F
Humidity:	30 % to 70 % RH
Max. altitude:	2000 m / 6562 ft
Electrical	
Power supply:	• 100-240 V~ 50/60 Hz • USB Type-C 5 V, 1 A
Power consumption:	< 5 W
Output circuit ratings:	Max. 240 V~, max. 5 A (5 A relay in power base)
Wi-Fi / Bluetooth:	Wi-Fi 6 dual band 2412-2472 / 5150-5850 MHz, < 20 dBm Bluetooth 5.0, 2402-2480 MHz, < 8 dBm